



Program 3 Expansion Pack

a sound enhancing expansion pack for the Roland **TD-20X**

a.k.a.

(Expanded TD-20 = TDW-20 Card equipped TD-20 Drum Module)

ALSO - *TD-30 compatible and additionally supported.*

Owner's Manual

End User License Agreement (EULA)

This is a legal agreement ("this Agreement") between you and V Expressions LTD., ("V Expressions LTD."). This Agreement pertains to your use of the V Expressions LTD. expansion programming, documentation and updates which are provided to you by V Expressions LTD (collectively, the "Product"). By purchasing a V Expressions LTD. Product, you are consenting to the terms of this Agreement.

This Agreement grants you a personal, exclusive, non-transferable, non-sub licensable right to use one copy of the V Expressions LTD. Product for your own personal use on a single computer and/or compatible drum module. V Expressions LTD. reserves all rights in the Product not expressly granted herein, including ownership and proprietary rights.

This software may not, in whole or in any part, be copied, reproduced, resold, transmitted, translated (into any language, natural or computer), reduced to any electronic medium or machine readable format, or by any other form or means without prior consent, in writing, from V Expressions LTD.

License Restrictions: You may not reproduce or distribute the Product. You may not copy the Product to any media, server or location for reproduction or distribution. You may not reverse engineer, de-compile or disassemble the Product or otherwise attempt to derive the source code for the Product, or without limitation, redistribute, sublicense, or otherwise transfer rights in the Product. This Product may not be rented, lent or leased. The restrictions contained herein apply equally to any updates that may be provided to you by V Expressions LTD..

Disclaimer of Warranties: Products provided by V Expressions LTD. are provided "As Is". V Expressions LTD. makes no warranty to you or any other entity.

Limitation of Liability: In no event shall V Expressions LTD. or its employees and/or partners be liable to you or any third party for any costs or damages arising directly or indirectly from the use of the V Expressions LTD. Product, including without limitation any actual, incidental, consequential, exemplary, punitive, reliance or special damages, or for any loss of revenue, profits, use, data, goodwill or business opportunities of any kind or nature whatsoever, arising in any manner from any cause or action or claim relating to this Agreement and to the Product provided by V Expressions LTD..

Indemnification: You agree to indemnify and hold V Expressions LTD., its employees and partners harmless from and against any and all damages, losses, costs including attorney fees and expenses resulting from any violation by you of this Agreement or asserted by any third party due to or arising out of your use of or conduct with respect to the Product.

Jurisdiction and Other Provisions: This Agreement and the relationship between V Expressions LTD. and you shall be governed in accordance with the laws of the State of Florida. Any dispute between you and V Expressions LTD. regarding this Agreement will be subject to the exclusive jurisdiction of the state and federal courts in the State of Florida.

You acknowledge that you have read this Agreement and understand it and that, by purchasing and/or using the product, you agree to be bound by its terms and conditions.

V Expressions LTD. products are the Intellectual Property of V Expressions LTD., its employees and/or partners. Violators of Intellectual Property rights will be prosecuted.

Copyright © 1997-2009, 2023 V Expressions LTD.

Introduction to the TD20X / TD30 / TDW-20 PLATFORM

Thank you for purchasing V Expressions LTD's **Program 3 Expansion Pack!**

Program 3 Expansion Pack is the latest edition to the Program series and fully supports the TDW-20 equipped TD-20 (a.k.a. **TD-20X**) and the **TD-30**.

NOTE: Not compatible with an original TD-20 operating system.

It will not work in a non-expanded TD-20, nor will this file be able to transfer to a TD-12 using V Drum Librarian.

This expansion pack is a collection of **kits that can be used in both live and recording situations** by hobbyists, weekend warriors and professionals alike. Professional gigging and recording v-drummers can expand their library of custom kits to accommodate many musical genres, eras and types of drums. This expansion is **fully customizable** allowing the user to continue adjusting the kits, triggers and calibrations to best match his or her playing style.

What this expansion pack IS...

Program 3 is based on studio recordings, specific source tambré and tunings, artist drum kits, and Live Ambiences found in most venues. All of these drum kits have been ear-created from scratch on the TDW-20 platform, and are modeled closely to the source recordings or the actual drum kits the programmer played.

There are **15 recently released Hard Rock/Metal genre kits** as well as **5 current R&B kits** to select from. There are also **17 newly created custom drum kits** from the original source drum sets. These kits are very high-end custom drum sets that are generally built to order and are one-offs from their respective shops. In addition, this pack offers **10 Live kits** that have been created and tested on a (PA) loudspeaker system. These are ready for immediate live use. Additionally, you will get **2 Electronic kits** and a **World Percussion** set up that is dynamite!

As with all our TD20 offerings, this expansion has been **designed to achieve maximum flexibility in multiple situations and environments.** The design of this expansion pack **allows v-drummers full access to ambience and effects with complete output control in live and studio environments.**

Although ambience and general reverb effects have been added to all kits to enhance their sound in a specific environment, these settings can easily be turned off and/or adjusted up or down by the drummer if a different tonal environment is desired.

Program 3 Tips & Tricks

The **Program 3 Expansion Pack** has been designed with total flexibility in mind. Using **both** the wave board sounds and standard operating system, combined with the enhancements of the **TDW-20 card/ expansion board**; you will find these kits both useful and practical for all of your playing experiences.

These kits are designed to sound **live and very ambient.** Ambience and effects can be turned off, up or down based on each individual's desire. Some tweaking for your personal P.A. system and/or headphones may be required to achieve the results you desire.

Kit description:

Kits 1-10 are designed for “Live” use through a PA. These kits are directly modeled from our “Live Kit” arsenal. Their overall volumes can be devastating. The kit volumes have been set to 100 with extra headroom up to 127 depending on your system capabilities. For large, high-end systems, adjusting the kit volumes to 127 is recommended to feel the drums in your chest and body. Each of these kits (with the exception of the 2 Jazz kits) can easily do this and has been tested on a PA. Like with their acoustic counterparts, these kits may damage speaker components and cause severe ear damage, so please use caution when testing out on a loud PA system. Start out quiet and bring up volumes accordingly.

Kits 11-25 have been ear created to closely match the Artist Recorded Sound when possible. These particular Hard Rock/Heavy Metal kits are found nowhere else in our current libraries. All original source recordings have been custom modeled to the best of the TD-20X (TDW-20 equipped TD20) capabilities. Ambience and Master Effects have been utilized to best suit the drum kit in the studio environment where it was recorded. Eq'ing and Compression have been minimalized to let the drum kits remain ambient.

Kits 26-30 are the R&B (Rhythm and Blues or Beat) modeled set ups. These come from current Artists recorded sound. The overall volumes of these kits have been set to 110.

Kits 31-47 are the custom shop one-off drum kits. From various famous makers and not so famous, these drum sets will satisfy even the die-hard acoustic drum set fans. Australian made Spirit Drums, Barrel Stave Lignum Drums, and even the oldest US manufacturer of drums: Noble & Cooley; all these sets have been modeled from the actual drum set itself or high-quality studio samples obtained around the globe.

Kits 48/49 are electronic drum sounds. Very 80's in nature, with a signature sound, you'll find these kits both useful and fun to add to your repertoire of kits.

Kit 50 is a World Percussion set up. Jam using terrific African, Latin, European, and Asian instruments, all combined to provide a diverse and ethnic collection of sounds.

Useful tips using Program 3:

SNARE: To achieve a well-rounded and cutting snare sound, we have adjusted the compression gain output to maximize the ambient nature of these Roland PCM samples. For better definition and uniform tone, we recommend adjusting the mic placement, as well as shell size / type to dramatically change the overall nature of the drum sound. To even up your sticking volumes, we recommend adjusting the compression ratio's all the way up to 50:1. This will result in a more unilateral controlled sound and volume, and is great for recording purposes.

TOMS: You will notice that the toms may cut through far greater on this pack than any other created in our libraries (to date: 2009). This platform has taken advantage of a low compression output with very High Gain Eq'ing technique. The mid-range quotients are set higher than what is normally expected. This results in an excellent attack, with fantastic tone and tambre follow through. Most shells will naturally reverberate on a specific tone and that waveform can be viewed on a Spectrum Analyzer. This eq and compression technique has been modeled in a similar fashion. We used an Audio Control SA3052 and the IZOTOPE RTA to capture and store the waveforms of the toms we modeled directly from the source shells. We used that waveform to closely match our ear-created toms on the TD20X / TDW-20, all while monitoring in Pro Tools HD for both sound and a visual scope.

This is what makes the Program 3 platform so unique.

CYMS: Most Cymbal sets have been matched for Live Performance. We strongly recommend using our set ups as a starting point to create your own personal cymbal sets. Mic placement, Eq'ing and Ambience will play a large factor in the overall produced sound out of the module. Some of **Program 3's** volumes for cymbals have been adjusted lower than normal to compensate for this. A quick mixer adjustment will bring these cymbals louder or softer to better suit your requirements.

SETUP NOTES:

FADER VOLUMES to start: TD-20X and TD-30

Please set your group faders to around 70% before loading your backup or individual kits, as this will yield the best volume results. Make adjustments to the sliders to affect the global volumes of each instrument set.

TD-20X:

Program 3 comes as a standard TDW-20 backup. **(TDW2BK12.TD0)**

TD-30:

TD30 compatibility is supported. **(TD30_Backup012.TD0)**

Aux 1 is programmed as a higher pitched tom to the other 4 Toms (Toms 1-4). If you are using Aux 1 as a cymbal or other effect pad, you can easily make adjustments in VDL or by using the copy feature to set to the desired sound.

Aux 2-4 have been programmed as various cymbals.

The **Hi-Hat** has been programmed using the VH12 Hat system.

Please read the following:

The information below is crucial to getting the most out of Program 3 with your TDW-20 equipped TD-20.

The setup information file that comes standard with the backup has been taken from a **Roland Default** setup.

We strongly recommend you open the backup in VDL and copy your setup file from a previous backup, then resave the file. This will preserve the settings and volumes directly from your drum set, and the pack parameters will adjust to these settings accordingly.

VDL = V Drum Librarian
www.vdrumlib.com

Note:

If you do not use VDL, take a moment to write down your Trigger settings, as loading our backup directly from your CF card will result in "resetting" your parameters to a Roland Default set up.

Thank you once again for purchasing the **Program 3 Expansion Pack** from **V Expressions LTD**. We hope you enjoy it!

Program 3 Kit Listings:

1. Live Birch – 1996 Tama Starclassic Birch
2. Live Mahog – 1985 Premier Resonator
3. Live Brush – Brush kit based on a 2009 DW Classic
4. Live Maple – 1999 Noble and Cooley CD Maples
5. Live Timbales – Tito Puentes Latin derived kit
6. Live Exotics – 2005 DW Tamo Ash w/ maple core shells
7. Live Contemporary – 1994 Tama Cordia II
8. Live Combo – 1987 Yamaha Touring Combination shell kit
9. Live Jazz – Standard 60's Sonor Vintage Jazz kit
10. Live Tight – Standard 1999 Mapex Orion Maple Fusion kit
11. Tool - 10K Days Album – Song: The Pot
12. The Killers – Song: Mr. Brightside
13. Maroon 5 – Song: Harder to Breathe
14. Metallica 08 – Album –Death Magnetic
15. Disturbed 09 – Song: The Night
16. New Found Glory – Song: Not without a fight
17. Burn Halo – Album: Burn Halo
18. Queensryche 09 – Song: If I were King
19. All that Remains – Artist: Jason Costa
20. Killswitch Engage – Song: Holy Diver cover
21. Avenged Sevenfold – Album: City of Evil
22. As I lay Dying – Artist: Jordon Mancino
23. Sylosis – Artist: Rod Callard
24. Silverstein – Artist: Paul Koehler
25. Symphony X – Artist: Jason Rullo
26. R&B 1 – Song: Dead & Gone by T.I./ Justin Timberlake
27. R&B 2 – Song: Magnificent by Rick Moss/ J. Legend
28. R&B 3 – Song: Mad by Ne-Yo
29. R&B 4 – Song: Halo by Beyonce
30. R&B 5 – Song: Birthday Sex by Jeremih
31. Pearl Reference – 2009 Maple birch shell mix - 22/14/8/10/12/14/16
32. 1982 Ludwig Chrome Classic – 24/14/10/12/14/16/18
33. Premier Genista 1997 – 20/13/8/10/12/13/14
34. Sonor S Classix 2009 – 22/14/8/10/12/14/16
35. Ddrum Dominion 2008 – 26/14/8/10/12/14/16
36. Tama Exotic Bubinga 2006 – 22/14/10/12/13/14/16
37. Gretsch Brodkaster 2009 – 20/12/12/14 (additionally modeled: 8/10/16)
38. Fortune Custom Drums 2008 – 20/13/8/10/12/14/16
39. Noble & Cooley Horizon Limited Edition 2009 – 22/13/8/10/12/14/16
40. Spirit Custom Drums – Australia made: 2008 – 20/12/8/10/12/14/16
41. Shine Custom Drums – 2008 –20/13/10/12/13/16/18
42. Truth Custom Drums – 2009 – 22/14/8/10/12/13/16
43. Six Gun Drums – 2008 - 24/14/8/10/12/14/16
44. Bison Drums – 2009 – 24/14/8/10/12/14/16
45. Epiarch Drums – 2008 – 22/14/12/13/14/15/16
46. Mullins Drums – 2009 – 22/12/8/10/12/13/16
47. Lignum Drums – 2008 – Barrel Stave / Segmented Shell drums
48. 808 Revised – Roland TR808 based with 80's classic E-toms added
49. Phased R&B – Roland TR909 derived with phaser effect
50. World Spirit – World Percussion set up

TD-20X / TDW-20 Equipped TD-20 Expansion Pack Instructions

File you will use is: **TDW2BK12.TD0**
Transfer this file to your computer

READ ALL OF THE FOLLOWING BEFORE CONTINUING!

All user kits (51-100) in your TD-20X (flash memory) **will be overwritten during a load of any backup file from a CompactFlash card or midi transfer**. The factory reset information is not disturbed and the original version of the TD-20X can be reset at any time to return to your default purchased starting point.

We highly recommend backing up your current module's memory to save any personal previous changes before loading any expansion packs from V Expressions LTD. You will also be able to load individual sets as described below.

Please take a moment to read all of our procedures below before attempting them.

If you have questions before attempting any of the procedures below, please refer to your TD-20X (and TD-20 w/ TDW-20) owner's manual or email V Expressions LTD from our website at www.vexpressionsltd.com.

Formatting a New CompactFlash Card

- Step 1:** Insert a CompactFlash card into the card slot on the module's front panel.
- Step 2:** Press [CARD]. The CompactFlash indicator light, and the "CARD MENU" screen appears.
- Step 3:** Press [F4 (FORMAT)]. The "CARD FORMAT" screen appears.
- Step 4:** Press [F5 (EXECUTE)]. The confirmation screen appears. *To cancel, press [F1 (CANCEL)].*
- Step 5:** Press [F5 (EXECUTE)] again to start formatting.

Saving a Backup via CompactFlash

- Step 1:** Insert a formatted CompactFlash card into the card slot on the module's front panel.
- Step 2:** Press [CARD]. The "CARD MENU" screen appears.
- Step 3:** Press [F1 (SAVE)]. The "CARD SAVE" screen appears.
- Step 4:** Use [+/-] or [VALUE] to select a backup to which you want to save the data. *You can select an empty backup area with the lowest number by pressing [F4 (NEW)]. Do not use backup 12.*
- Step 5:** Press [F5 (SAVE)]. The confirmation screen appears. *To cancel, press [F1 CANCEL)].*
- Step 6:** If you want to change the name of the backup area, press [F4 (NAME)].
- Step 7:** Press [F5 (EXECUTE)] to save the data.

Transferring Expansions to a CompactFlash card from a computer

Important! If your card contains previous backups, rename the newly supplied file(s) to different back up numbers. (*i.e.: TDW2BK12.TD0 to TDW2BK13.TD0*). TD-20X can Read/Save to # 01-99.

- Step 1:** Insert a formatted CompactFlash card into a card reader connected to the computer.
- Step 2:** Extract all files from the supplied expansion pack zip file to a folder on your computer.
- Step 3:** Copy the expansion "TD0" file(s) to the Roland/TD folder found on the CompactFlash card.

The File you want is: TDW2BK12.TD0 - copy/paste this file to TD Folder on CF Card.

TD Folder is one click past the Roland Folder.

Loading Expansions from a CompactFlash card

This procedure **will not** preserve trigger settings you may already have changed in your module and/or setup. **By loading an entire backup file, you may need to adjust trigger types and calibrations to achieve the best volumes, calibration and sound the programmer intended.** You can skip to individual load below instead, but will take a lot longer.

Tip-Use [VDrumLib](#) to quickly copy preferred “setup information” from personal backups.

Step 1: Insert the CompactFlash card into the card slot on the module’s front panel.

Step 2: Press [CARD]. The CompactFlash indicator lights and the “CARD MENU” screen appears.

Step 3: Press [F2 (LOAD)]. The “CARD LOAD” screen appears.

Step 4: Use [+/-] or [VALUE] to select / Scroll to **Bank or Backup 12 – Program 3 (PGM 3)**

Step 5: Press [F5 (LOAD)]. The confirmation screen appears. *To cancel, press [F1 (CANCEL)].*

Step 6: Press [F5 (EXECUTE)] to load the data.

We recommend you check all your pad types and correct any mis matches.

Then re-calibrate your Roland Hi Hat (only VH10, 11, 12, or 13). FD pedal users can skip this.

Save a Backup to your CF card with the new settings you just performed.

Loading Individual Kits from a CompactFlash card

Hint: This procedure is **a great way to preserve** trigger settings you may already have changed in your TD-20X module and/or setup. **By loading individual kits, your trigger types and calibrations will be preserved.** *Some minor adjustments may be needed to accommodate your playing style.*

Step 1: Insert the CompactFlash card and Press [COPY]. The “COPY” screen appears.

Step 2: Press [F1 (KIT)] to select drum kit.

Step 3: Use [CURSOR], [+/-], or [VALUE] to select the copy-source (Bank 12 kits) and the copy-destination.

Step 4: Press [F5 (COPY)]. The previous content of the destination is overwritten by the new content of the source. The confirmation screen appears. *To cancel, press [F1 (EXIT)].*

Step 5: Press [F5 (EXECUTE)] to carry out the procedure.

TD-30 Expansion Pack Instructions

File you will use is: **TD30_Backup012.TD0**

Transfer this file to your computer

Saving Your V Expressions LTD download file to your USB Drive

Step 1: Insert your formatted USB drive into your computer.

Step 2: From your Desktop, locate the file: **TD30_Backup012.TD0**

Step 3: Open your USB drive and locate the Roland Folder and Dbl Click

Step 4: A TD-30 Folder will appear, DBL click that

Step 5: A Backup Folder will appear, DBL Click that

Step 6: Select and drag desired file into this folder.

Step 7: Verify that the file is there.

Step 8: Once verified the file is there, back out of screen and Properly EJECT the USB Drive

V Expressions LTD recommends Auditioning the Expressions 1 kits from the USB Drive before loading any files to your module.

Preserve your trigger settings and audition each kit from the USB thumb drive.

Audition/Copy any drum kit in Program 3 on the TD-30 without loading

See pg 123 in your TD-30 manual

Step 1: Press Setup

Step 2: Press F5 scroll to B [A↔B] button for (KIT SEL)

Step 3: Press F1 KIT SEL

Step 4: Press F3 USB

Step 5: Press F3 to scroll to bank (12)

Step 6: Use Value Dial to audition the kits (1-50)

Step 7: To Copy kit into USER section, press F5 Copy

Step 8: Use Value Dial to Select a USER kit (1-100)

Step 1: Press F5 Copy

Step 1: Press F5 Execute

Use the Kit Copy function to load each kit individually.

Copying each kit individually to the TD-30

See pages 49 & 50 in your TD-30 manual

Step 1: Connect your USB flash drive into the module's USB Memory Port.

Step 2: Press Shift and the USB MEM button together

Step 3: Press F1 Kit

Step 4: Press F3 USB

Step 5: Set Bank to PGM 3: Scroll to bank (12)

Step 6: Set USB to any VEX kit (1-50)

Step 7: Set USER to any kit of your choice (1-100)

Step 8: Press F5 (copy / execute)

Repeat this process for each kit you want to load individually.

V EXPRESSIONS LTD TD-20X TROUBLESHOOTING GUIDE

Symptom: The module does not recognize the CF card.

Remedy 1: New CF cards must be formatted by the module. (Format card)

Remedy 2: The (Original TD-20) module could only read CF cards up to 512mb in size. If you are using a larger size card, the module may not recognize it due to this limitation. (Use 512mb or smaller ***)

*** If still an issue - try a different CF Card 64 – 512mb in size. Look on Amazon.com to find these.

*** If the Module CF Card Reader Light isn't coming on after you press CARD – There is a hardware problem with module. Visit: **Roland.US** for service centers near you.

Symptom: The module says there is “no data” on CF Card.
Remedy: Common mistake: Putting zip file on card without extracting files.

The module cannot read “zip” files. We use packet zip files to contain all your files for the pack. Extract your expansion files from the original downloaded zip file and continue with the directions in Section 3, Step 2 of this manual. For more help with extracting zip files, please search the web for a free zip extracting tool or read your windows/mac operating system’s help file.

Symptom: I've extracted the zipped files and put them on the card, but the module still says there is **no data**.
Remedy: The “**TDW2BK12.TD0**” file must be placed inside the **TD folder** found on your module-formatted CF card. If the TD0 file is not inside the **TD folder**, the module will not recognize it. The **TD Folder** is one click past the Roland Folder on the CF Card.

V Expressions LTD Contact Information

If you have questions before attempting any of the above procedures, please refer to your TD-20 owner’s manual or email V Expressions LTD from our website at www.vexpressionsltd.com.

Programmer Contact Information:

Expansion Pack	Programmer	Contact
Program 3	Chris Blood	email: fiddlebak@gmail.com

All programmed sounds are Trademarked © 1997-2009, 2023 V-Expressions LTD.
Copying, distributing and all unauthorized use of these sounds is strictly prohibited.